

## **General Description**

COMPEND 2000 is a PC compatible sequence programmable control and data acquisition system with software running under Windows 98, 2000, NT4 or XP. COMPEND is compatible with the Phoenix SUPERSLIM Serial Link Interface Module and a range of other digital devices include Froude Texcel V4 dynamometer controller, SSD digital drives (ac and dc), the HBM MGC torque transducer amplifier, the Coherent 3AXIS motion controller and the Data Translation DT3010 & DT300 series high-speed data acquisition cards. A maximum of four SUPERSLIM units plus an unlimited number of other digital devices may be connected to form a single system.

## **Features**

- Software configurable, sequence programmable control and data acquisition

- Common platform providing open systems architecture and connectivity

- Code free configuration/programming of Definition, Calibration and Sequence files

## **System Editor**

Allows user to configure the system to meet current requirements. Involves defining input and output channels, identifying units and scaling, creating derived channels and defining in which box and on which page of the multi-layer screen display information is to be displayed. Multiple boxes connected to a single common channel are permitted on multiple pages. Box sizes automatically adjust to fit the user defined screen area thus permitting high visibility displays of selected channels.

## **Test Sequence File**

Allows user to program continuous or sequence control. Steady state, ramped and software PID controlled outputs may be programmed. Data collection on analogue inputs may be programmed with up to eight data collections modes user selectable.

## **Alarm System**

Allows user to program high and low level warning and shut down alarms on all analogue, pulse counting and derived channels on step-by-step or global basis.

## **Data Files**

Data recorded in a format that may be read by PC compatible machines. Data files are comma separated variable (csv) or TAB separated variable

(tsv). May be imported directly into most spreadsheet software packages for post processing and report generation.

## Specification

Direct Set-points	YES
Direct Digital Control	YES
Software PIDs	YES
Number of Logical Steps	Unlimited
Number of Physical Steps	Up to 1000
Control Step Rate	up to 10 Hz
Internal Control Frequency:	1 kHz
External Control Frequency:	10 Hz
Data Acquisition Rate:	10 Hz (up to 2 SUPERSLIM) 5 Hz (up to 4 SUPERSLIM)
Resolution:	12 bit
System Maximum Capacity:	SUPERSLIM x 4
Data channels:	Base System/Maximum
Analogue In	8/32
Analogue Out	4/16
Digital In	4/16
Digital Out	4/16
Pulse Counting Inputs	2/8
Minimum System Configuration:	Pentium II 233 MHz 32 Mbytes RAM

## Interface Hardware

SUPERSLIM Serial Link Interface Modules

Digital Drives (ac, dc and ac servo)

Custom Configured Digital Devices

Data Translation 3010/300 Series High-Speed Multifunction Boards

Coherent Motion Controller

## TTI TG1010 Function Generator

### Facilities

Resident Editor

Run Time Editing

Active Test File Viewer

Pick from List File Selection

#### Programmable Data Collection:

1 Hz Sample Rate Single Average

10 Hz Sample Rate Single Average

10 Hz Sample Rate Peak Value

Continuous 1 Sample per 10 Minutes

Continuous 1 Sample per 1 Minutes

Continuous 1 Sample per 10 Seconds

Continuous 1 Sample per 1 Second

Continuous 1 Sample per 0.1 Seconds

#### Conditional Stepping:

Direction Sensitive

Derived Channels

#### Manual Stepping

Pause/Restart

User Definable Standby Set-points

Manual Data Channels

Analogue Channel Alarms

Pulse Counting Channel Alarms

Derived Channel Alarms

Complex Derived Channels

Real Time Auto Scaling Trending

History Graph Buffer

Data Transfer to Networked Devices

High Speed Data Acquisition Option